



ENGLISH

-The connection of this device must only be carried out by a qualified specialist.
-Input voltage range: 12C DC - 24V DC.
-Make sure that the device is correctly installed, as shown in the diagram.
-Cut off the connection to the mains during installation.
-The unit can only be used as a sensor switch for 12C DC - 24V DC, and is only suitable for indoor use.
-Protect the controller against humidity and heat.
-The temperature range for optimum operation of the sensor is -10 to +40° C.
-The maximum load connected to the sensor must be as specified.
-If the sensor is used for purposes other than those for which it was originally intended or is connected/installed incorrectly, the If the sensor is used for other purposes than originally intended or connected/installed in the wrong way, liability cannot be assumed for possible damage.
-Keep the sensor detector clean, to avoid undesired sensor actions.
-Make sure that the sensor detector is properly fixed, otherwise the function may be impaired.
-The flexible cable or outer cord of this device cannot be replaced, in case it is damaged, the device must be replaced.

BINDING AS RF RECEIVER (RADIO FREQUENCY - RF 2.4Ghz):

- 1- Press the link button A on the receiver (short press 1 second -1").
- 2- Immediately press the link button B on the transmitter (Short press 1 second -1").
- 3- When the luminaire flashes 3 times C, the transmitter and receiver are linked.
- 4- To link the 2nd,3rd,...6th transmitter with the same receiver, repeat step 2.

UNLOCKING RF RECEIVER (RADIO FREQUENCY - RF 2.4Ghz):

- 1- To unlink the transmitter or receiver, we must press the link button A (long press) for 10 seconds. It will be successfully unlinked when the luminaire flashes 3 times C.

LINK AS WIFI RECEIVER (WIFI - 2.4Ghz network):

- 1- Install the Smart Life app on the device from the app shop or by scanning the QR code.
- 2- Connect to a 2.4Ghz WIFI network (NOT valid for 5Ghz networks).
- 3- Connect the device's Bluetooth.
- 4- Press the link button A on the WIFI module (IOT). (Long press for 5 seconds -5").
- 5- Open the Smart Life application on the device.
- 6- Inside the application, click on the + symbol to add device.
- 7- The application will find the new device. Click on ADD (You can also add it manually by searching in the lighting section for the device: Strip lights (BLE+Wi-Fi)).
- 8- You can edit the name of the device from the application.
- 9- In the menu of the new device, select the option: SINGLE and you will be able to adjust the brightness or switch the device on and off from the application.
- 10- To link the Smart Life application to a voice assistant, this has to be done from the application of the chosen voice assistant.
- 11- To UNBIND the device, this must be done from the Smart Life application, deleting the device.

THIS DEVICE COMPLIES WITH EUROPEAN LEGISLATION

PORTUGUÊS

-A ligação deste aparelho só pode ser efectuada por um técnico qualificado.
-Gama de tensão de entrada: 12C DC - 24V DC.
-Certifique-se de que o aparelho está corretamente instalado, como mostra o esquema.
-Cortar a ligação à rede eléctrica durante a instalação.
-A unidade só pode ser utilizada como interruptor de sensor para 12C DC - 24V DC, e só é adequada para utilização em interiores.
-Proteger o controlador contra a humidade e o calor.
-A gama de temperaturas para um funcionamento ótimo do sensor é de -10 a +40° C.
-A carga máxima ligada ao sensor deve ser a especificada.
-Se o sensor for utilizado para outros fins que não aqueles para os quais foi originalmente concebido ou se for ligado/instalado incorretamente, a carga máxima ligada ao sensor deve ser a especificada.
Se o sensor for utilizado para outros fins que não aqueles para os quais foi originalmente concebido ou se for ligado/instalado incorretamente, não pode ser assumida a responsabilidade por eventuais danos.
-Manter o detetor de sensores limpo, para evitar acções indesejadas do sensor.
Certifique-se de que o detetor de sensores está corretamente fixado, caso contrário o seu funcionamento pode ser prejudicado.
-O cabo flexível ou o cabo exterior deste dispositivo não podem ser substituídos; em caso de danos, o dispositivo deve ser substituído.

LIGAÇÃO COMO RECEPTOR DE RF (FREQUÊNCIA DE RÁDIO - RF 2,4Ghz):

- 1- Premir o botão de ligação A do recetor (pressão curta 1 segundo -1").
- 2- Premir imediatamente o botão de ligação B no emissor (premir brevemente 1 segundo -1").
- 3- Quando a luminária piscar 3 vezes C, o emissor e o recetor estão ligados.
- 4- Para ligar o 2º, 3º,...6º emissor ao mesmo recetor, repetir o passo 2.

DESBLOQUEIO DO RECEPTOR RF (FREQUÊNCIA DE RÁDIO - RF 2.4Ghz):

- 1- Para desbloquear o emissor ou o recetor, devemos premir o botão de ligação A (pressão longa) durante 10 segundos. A desvinculação será efectuada com sucesso quando a luminária piscar 3 vezes C.

LIGAÇÃO COMO RECEPTOR WIFI (rede WIFI - 2.4Ghz):

- 1- Instalar a aplicação Smart Life no aparelho a partir da loja de aplicações ou digitalizando o código QR.
- 2- Ligat a uma rede WIFI de 2,4Ghz (NÃO é válido para redes de 5Ghz).
- 3- Ligat o Bluetooth do aparelho.
- 4- Premir o botão de ligação A no módulo WIFI (IOT). (Premir longamente durante 5 segundos -5").
- 5- Abrir a aplicação Smart Life no aparelho.
- 6- Na aplicação, clicar no símbolo + para adicionar um dispositivo.
- 7- A aplicação encontra o novo dispositivo. Clique em ADICIONAR (também pode adicioná-lo manualmente, procurando o dispositivo na secção iluminação: Fita luminosa (BLE+Wi-Fi)).
- 8- Pode modificar o nome do dispositivo a partir da aplicação.
- 9- No menu do novo dispositivo, seleccione a opção: SINGLE e poderá regular a luminosidade ou ligat e desligat o dispositivo a partir da aplicação.
- 10- Para associar a aplicação Smart Life a um assistente de voz, deve fazê-lo a partir da aplicação do assistente de voz escolhido.
- 11- Para DESVINCULAR o aparelho, isso deve ser feito a partir da aplicação Smart Life, apagando o aparelho.

ESTE APARELHO ESTÁ EM CONFORMIDADE COM A LEGISLAÇÃO EUROPEIA